

CREATE YOUR PART NUMBER

1	2	3A	4	3B	5	6	7
MS27468	T	25	F	35	P	A	-LC
SHELL STYLE	CLASS	SIZE	PLATING	LAYOUT	CONTACT	POLARIZATION (OMIT FOR NORMAL)	MODIFIER

(military part number example) *Note: Out of sequence

WHEN CHOOSING LAYOUT

First Number = Step 3A – Shell Size, Dash = Step 4 – Plating, Second Number = 3B – Layout

1	2	3	5	6	4*	7
LJT07	RE-	25-35	P	A	-014	-LC
SHELL STYLE	CLASS	LAYOUT	CONTACT	POLARIZATION (OMIT FOR NORMAL)	PLATING*	MODIFIER




(Commercial part number example)

STEP 1: SELECT SHELL STYLE, PLUG OR RECEPTACLE





RECEPTACLES

Mates with

PLUGS

**MS27466
(LJT00R)**Front Mount
with Rear
Accessory Threads.**MS27656
(LJTPQ00R)**Rear Mount
with Rear
Accessory Threads.**MS27467
(LJT06)**

Available with PC pins. Contact us for details.

**MS27496E
(LJT02RE)**Front Mount
without Rear
Accessory Threads.**MS27505E
(LJTP02RE)**Rear Mount without Rear
Accessory Threads.**MS27468
(LJT07R)**Jam Nut with Rear
Accessory Threads.**(LJT01R)**In-line with
Accessory Threads.

STEP 2: SELECT CLASS

**E°** = No rear accessories**P°** = Potting ring & cup**T°** = No rear accessories, NOT used on MS27505E & MS27496E**RE** = No rear accessories**RP** = Potting ring & cup**RT** = No rear accessories, NOT used on LJT02RE & LJTP02RE**RGF** = Electroless nickel-plated ground-plane aluminum 200°C**RGW** = Olive drab cadmium-plated ground-plane aluminum

° Military + Most Popular

STEP 3: SELECT LAYOUT

Layout	Service Rating	Contacts													Specials		
		Total	22D	22M	22	20	16	12	8	4	2/0	12*	10	8*	8**		
9-6	M	6		6													
9-35	M	6	6														
9-45	M	4			4												
9-98	I	3				3											
11-2G	I	2					2										
11-4♦	I	4				4											
11-5♦	I	5				5											
11-12(11-01)		1						1									
11-13	M	13		13													
11-35	M	13	13														
11-98	I	6				6											
11-99	I	7				7											
13-3P♦	II	3					3										
13-4G	I	4					4										
13-8	I	8				8											
13-22	M	22		22													
13-26	M	8	6					2									
13-35	M	22	22														
13-98	I	10				10											
15-4♦♦	I	4						4									
15-5G	II	5					5										
15-15	I	15				14	1										
15-18	I	18				18											
15-19♦	I	19				19											
15-35	M	37	37														
15-37	M	37		37													
15-68♦♦	I	8					8										
15-97	I	12				8	4										
17-2♦	M	39	38													1	
17-6	I	6						6									
17-8G	II	8					8										
17-13♦♦	I	13					13										
17-22♦♦	COAX	4									2		2				
17-25♦♦	M	24	22										2				
17-26	I	26				26											
17-35	M	55	55														
17-42♦	M	42			42												
17-55	M	55		55													
17-75	I	2														2	
17-99	I	23				21	2										
19-11G	II	11					11										
19-18♦	M	18	14													4	
19-28		28				26	2										
19-30P♦	I	30				29	1										
19-32	I	32				32											
19-35	M	66	66														
19-53P♦	M	53			53												
19-66	M	66		66													
19-67♦♦P	M	67		67													
19-68♦♦P	I	18				18											
21-1	M	79		79													
21-2♦♦	M	65			65												
21-11♦G	I	11						11									
21-16G	II	16					16										
21-35	M	79															
21-39	I	39				37	2										
21-41	I	41				41											
21-48		4							4								
21-75♦G	N	4														(See Note 4)	
21-79♦♦	II	19	17													(See Note 5)	
23-1	M	100		100													
23-2	M	85			85												
23-6P♦G	M	6														6	
23-14♦♦	I	14						14									
23-21G	II	21					21										
23-32P♦	I	32				32											
23-35	M	100	100														
23-53	I	53				53											
23-55♦	I	55				55											
23-P1(23-01)		1									1						
25-1	M	128		128													
25-2	M	100			100												
25-4	I	56				48	8										
25-7♦♦	M	99	97													2	
25-11S♦♦	N	11				2							9				
25-19♦G	I	19						19									
25-20♦♦	N	30				10	13				4				3		
25-24G	I	24					12	12									
25-29G	I	29					29										
25-35	M	128	128														
25-37♦♦G	I	37					37										
25-43♦	I	43				23	20										
25-46♦	I	46				40	4									(See Note 6)	
25-61	I	61				61											
25-1AC(24-44)	M	8					4			4							

For listing by # of contacts, ⇨ see pages 178-181.

STEP 4: SELECT PLATING

Finish	Military	Commercial	Commercial +SR
Cadmium-plated nickel base	A	-	SR
Olive drab cadmium-plated nickel base	B	014	386
Electroless nickel	F	023	424
Electroless nickel space-compatible	-	453	467
Anodic coating (Alumilite)	C	005	300
Chromate-tested (Iridite 14-2)	-	011	344
Passivated steel (Hermetic only)	E	-	-
Stainless steel	-	155	-
Olive drab zinc cobalt	-	W52	-

SR = Strain Relief


STEP 5: SELECT CONTACT

P = Pin
S = Socket
H = 1500 Mating Cycles Pin

J = 1500 Mating Cycles Socket
A = Less Pin Contacts
B = Less Socket Contact

STEP 6: SELECT POLARIZATION

N = Normal Standard (Omit for normal)
A = Highly-Popular
B = Limited Availability
C = Check for Availability
D = Check for Availability



Mating Face of Receptacle

Shell Size	N	A	B	C	D
9	95	77	-	-	113
11	95	81	67	123	109
13	95	75	63	127	115
15	95	74	61	129	116
17	95	77	65	125	113
19	95	77	65	125	113
21	95	77	65	125	113
23	95	80	69	121	110
25	95	80	69	121	110

STEP 7: SELECT MODIFIER

Note: LC is not marked on part**Omit** for standard contacts**LC** = less contacts, wire hole fillers and plastic insertion/extraction tool.

(Purchase Order must state Less Contacts)

(4) MS Connector 21-75 is supplied with four size-8 twinax contacts. Proprietary connector 21-75 is supplied with four size-8 coax contacts.

(5) MS connector 21-79 has provision for two size-8 coax contacts. Coax contacts are not supplied unless specified by customer.

(6) 25-46 is supplied two size-8 coax contacts for RG180/U & RG195/U cable.

***** NOT QPL'D ♦ Not Toolled for RP or 02RE **P** = Pin Insert Only
***** Coax ****** Twinax **S** = Socket Insert Only
G = Grounded

HOW TO ORDER HE308 SERIES CONNECTORS

1	2	3	4	5	6	7	8	9
HE308	07	T	1535	P	N	7	M	L
PREFIX	SHELL STYLE	CLASS	LAYOUT	CONTACT	POLARIZATION	FINISH	MANDATORY SUFFIX	MODIFIER

(military part number example)

STEP 1: SELECT SHELL STYLE, PLUG OR RECEPTACLE

RECEPTACLES ← Mates with → PLUGS



00
Wall Mount Receptacle,
crimp contacts



01
Line Mount Receptacle,
crimp contacts



06
Straight Plug, crimp contacts



07
Jam Nut Receptacle,
crimp contacts



11
Jam Nut Receptacle,
PCB contacts

STEP 2: SELECT CLASS

T = Environmental with accessory thread

STEP 3: SELECT LAYOUT

For listing by # of contacts, ➔ see pages 178-181.

LAYOUT NUMBER	SERVICE RATING	CONTACTS								SPECIALS							
		TOTAL	22D	22M	22	20	16	12	12*	10	8*	8**	8 POWER	4	00		
9-22	I	2				2											
9-35	M	6	6														
9-98	I	3				3											
11-02	I	2					2										
11-04	I	4				4											
11-05	I	5				5											
11-01	-	1						1									
11-35	M	13	13														
11-98	I	6				6											
11-99	I	7				7											
13-04	I	4					4										
13-08	I	8				8											
13-26	M	8	6					2									
13-35	M	22	22														
13-98	I	10				10											
15-04	I	4						4									
15-05	II	5					5										
15-15	I	15				14	1										
15-18	I	18				18											
15-19	I	19				19											
15-35	M	37	37														
15-97	I	12				8	4										
17-02	M	39	38									1					
17-06	I	6						6									
17-08	II	8					8										
17-25	M	24	22							2							
17-26	I	26				26											
17-35	M	55	55														
17-75	I	2										2					
17-99	I	23				21	2										
19-11	II	11					11										
19-18	M	18	14									4					
19-28	I	28				26	2										
19-32	I	32				32											
19-35	M	66	66														
21-11	I	11						11									
21-16	II	16					16										
21-35	M	79	79														
21-39	I	39				37	2										
21-41	I	41				41											
21-48	-	4													4		
21-75	N	4										(See Note 4)					
21-79	II	19	17									(See Note 5)					
23-01	M	-	1													1	
23-21	II	21					21										
23-35	M	100	100														
23-53	I	53				53											
23-55	I	55				55											
25-04	I	56				48	8										
25-07	M	99	97									2					
25-19	I	19						19									
25-24	I	24					12	12									
25-29	I	29					29										
25-35	M	128	128														
25-37	I	37					37										
25-43	I	43				23	20										
25-46	I	46				40	4				2						
25-61	I	61				61											
25-44	M	8					4								4		

* COAX ** TWINAX

(4) MS Connector 21-75 is supplied with four size-8 twinax contacts. Proprietary connector 21-75 is supplied with four size-8 coax contacts.


(5) MS connector 21-79 has provision for two size-8 coax contacts. Coax contacts are not supplied unless specified by customer.

STEP 4: SELECT CONTACT

P = Pin S = Socket

STEP 5: SELECT POLARIZATION

N = Normal Standard
 A = Highly-Popular
 B = Limited Availability
 C = Check for Availability
 D = Check for Availability

Mating Face of
Receptacle

Shell Size	N	A	B	C	D
9	95	77	-	-	113
11	95	81	67	123	109
13	95	75	63	127	115
15	95	74	61	129	116
17	95	77	65	125	113
19	95	77	65	125	113
21	95	77	65	125	113
23	95	80	69	121	110
25	95	80	69	121	110

STEP 6: SELECT SHELL FINISH

7 = Olive drab cadmium-plated
 6 = Electroless nickel-plated

STEP 7: MANDATORY SUFFIX

M = Mandatory Suffix

STEP 8: MODIFIER

Leave blank for connector delivered WITH contacts

L = Connector delivered WITHOUT contacts

LAYOUTS BY NUMBER OF CONTACTS

View of Mating-Face of Pin Insert




Drawing not to scale; mating face view of pin insert shown (socket view is opposite)

CONTACTS	1	2	3	4					
LAYOUT # OF CONTACTS SERVICE RATING									
	11-12 1-#12 -	23-P1 (23-01) 1-#00 -	9-22 2-#20 I	11-2 ♦ G 2-#16 I	17-75 2-#8** I	9-98 3-#20 I	13-3 P♦ 3-#16 II	9-44 4-#22 M	11-4 ♦ 4-#20 I
CONTACTS	4				5				
LAYOUT # OF CONTACTS SERVICE RATING									
	13-4 G 4-#16 I	15-4 ♦ 4-#12 I	17-22 ♦ 2-#12* 2-#8* COAX	21-48 4-#8 Power -	21-75 ♦ G 4-#8** N	11-5 ♦ 5-#20 I	15-5 G 5-#16 II		
CONTACTS	6				7		8		
LAYOUT # OF CONTACTS SERVICE RATING									
	9-6 6-#22M M	9-35 6-#22D M	11-98 6-#20 I	17-6 6-#12 I	23-6 P♦ G 6-#8** M	11-99 7-#20 I	13-8 8-#20 I	13-26 6-#22D, 2-#12 M	
CONTACTS	8				10		11		
LAYOUT # OF CONTACTS SERVICE RATING									
	15-68 ♦ 8-#16 I	17-8 G 8-#16 II	25-1A (24-44) 4-#16, 4-#4 M	13-98 10-#20 I	19-11 G 11-#16 II				


















*Coax **Twinax • NOT QPL'D ♦ Not Tooled for RP or 02RE P = Pin Insert Only S = Socket Insert Only G = Grounded Contact us for more information.

LAYOUTS BY NUMBER OF CONTACTS

View of Mating-Face of Pin Insert




Drawing not to scale; mating face view of pin insert shown (socket view is opposite)

CONTACTS	11	12	13			
LAYOUT # OF CONTACTS SERVICE RATING	 21-11♦G 11-#12 I	 25-11S♦ 2-#20, 9-#10* N	 15-97 8-#20, 4-#16 I	 11-13 13-#22M M	 11-35 13-#22D M	 17-13♦ 13-#16 I
	CONTACTS	14	15	16	18	
LAYOUT # OF CONTACTS SERVICE RATING	 23-14♦ 14-#12 I	 15-15 14-#20, 1-#16 I	 21-16G 16-#16 II	 15-18 18-#20 I	 19-18♦ 14-#22D, 4-#8** M	
	CONTACTS	18	19	21		
LAYOUT # OF CONTACTS SERVICE RATING	 19-68P♦ 18-#16 I	 15-19♦ 19-#20 I	 21-79♦ 17-#22D, 2-#8* II	 25-19♦G 19-#12 I	 23-21G 21-#16 II	
	CONTACTS	22	23	24	26	
LAYOUT # OF CONTACTS SERVICE RATING	 13-22 22-#22M M	 13-35 22-#22D M	 17-99 21-#20, 2-#16 I	 17-25♦** 22-#22D, 2-#8 M	 25-24G 12-#16, 12-#12 I	 17-26 26-#20 I



















*Coax **Twinax • NOT QPL'D ♦ Not Tooled for RP or 02RE P = Pin Insert Only S = Socket Insert Only G = Grounded Contact us for more information.

LAYOUTS BY NUMBER OF CONTACTS

View of Mating-Face of Pin Insert



Drawing not to scale; mating face view of pin insert shown (socket view is opposite)

CONTACTS	28	29	30		
					
LAYOUT # OF CONTACTS SERVICE RATING	19-28 26-#20, 2-#16 I	25-29G 29-#16 I	19-30P 29-#20, 1-#16 I	25-20♦ 10-#20, 13-#16, 4-#12*, 3-#8** I	
CONTACTS	32	36	37		
					
LAYOUT # OF CONTACTS SERVICE RATING	19-32 32-#20 I	23-32P♦ 32-#20 I	23-36♦ 36-#20 I	15-35 37-#22D M	15-37 37-#22M M
CONTACTS	37	39	41	42	
					
LAYOUT # OF CONTACTS SERVICE RATING	25-37♦G 37-#16 I	17-2♦ 38-#22D, 1-#8** M	21-39 37-#20, 2-#16 I	21-41 41-#20 I	17-42♦ 42-#22 M
CONTACTS	43	46	53		
					
LAYOUT # OF CONTACTS SERVICE RATING	25-43♦ 23-#20, 20-#16 I	25-46♦ 40-#20, 4-#16, 2-#8** I	19-53P♦ 53-#22 M	23-53 53-#20 I	

*Coax **Twinax • NOT QPL'D ♦ Not Tooled for RP or 02RE P = Pin Insert Only S = Socket Insert Only G = Grounded Contact us for more information.

LAYOUTS BY NUMBER OF CONTACTS

View of Mating-Face of Pin Insert



Drawing not to scale; mating face view of pin insert shown (socket view is opposite)

CONTACTS	55	56	61
LAYOUT # OF CONTACTS SERVICE RATING	17-35 55-#22D M	17-55 55-#22M M	23-55 ♦ 55-#20 I
LAYOUT # OF CONTACTS SERVICE RATING	21-2 ♦ 65-#22 M	19-35 66-#22D M	19-66 66-#22M M
LAYOUT # OF CONTACTS SERVICE RATING	21-35 79-#22D M	23-2 85-#22 M	25-7 ♦ 97-#22D, 2-#8** M
LAYOUT # OF CONTACTS SERVICE RATING	23-35 100-#22D M	25-2 100-#22 M	25-1 128-#22M M
LAYOUT # OF CONTACTS SERVICE RATING	23-35 100-#22D M	25-2 100-#22 M	25-35 128-#22D M

*Coax **Twinax • NOT QPL'D ♦ Not Tooled for RP or 02RE P = Pin Insert Only S = Socket Insert Only G = Grounded Contact us for more information.